

Technical Note

mIP/IPDACT & VisorALARM CONTACT-ID events

mIP/IPDACT

Contact-ID Event	Description
110	mIP/IPDACT input activation
380	mIP/IPDACT sabotage
383	Tamper activation
351	PSTN supervisión detects line failure
330	Device <#> failed ETH monitoring
333	mIP/IPDACT hardware fault

VisorALARM PLUS & VisorALARM PLUS 2U

Contact-ID Event	Description
300	Hardware fault
301	Main power is lost
302	Low backup battery level
306	Intento de suplantación de mIP/IPDACT detectado
350	mIP/IPDACT connection lost
356	General communications failure
358	Backup receiver unreachable
393	Alarm storage capacity at 100%
394	mIP/IPDACT switches to backup receiver
395	mIP/IPDACT polls backup receiver
396	Local network failure
397	Network Time Protocol synchronization failure
399	Main receiver unreachable
621	Alarm storage LOG cleared
622	Alarm storage LOG capacity at 50%
623	Alarm storage LOG capacity at 90%
624	Alarm storage LOG overloaded
625	Performed Alarm storage LOG backup
633	mIP/IPDACT registered